

The TouchMi

- CO₂
- VPD
- Humidity
- Temperature
- Touch Screen



World's Smartest Controller

Dims lights if the temperature gets too high

Tracks blackouts for optimal lighting restart

TouchMi Specifications

The TouchMi is an intelligent controller that learns the size of the room for precise environmental monitoring.

Compatible Units

The TouchMi uses a low voltage digital data stream to switch, dim, and boost any Revolution, Phantom, MaxiBright or other ballasts equipped with a Revolution-style RS-485 data port.

FCC Part 15 B Certified, CE Certified, CSA Certified,
RoHS and RoHS2 Certified, **5 Year Warranty**



Cables

The TouchMi uses RJ-14 6P4C straight-through telephone (or data) cables. Our World Plug power supply adapts to your local outlets no matter where you are, right out of the box.

Dimming

The controller has built in sunrise and sunset functions to warm up plants as nature intended. The DEva 1000w HPS output power can be fine-tuned from 600W up to 1150W in 1% increments.

LED Spectrum Control

When using an Avici LED, the TouchMi has spectrum presets for Clone, Veg, Flower and Finish, and a programmable spectrum option where the Blue / White / Red levels go from 0-10 and can also be changed individually as desired for custom spectra.